

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

In re Patent Application of:  
**BRUNA ET AL.**

Serial No. **Not Yet Assigned**

Filing Date: **Herewith**

For: **A METHOD OF COMPRESSING  
DIGITAL IMAGES**

I HEREBY CERTIFY THIS PAPER OR FEE IS BEING  
DEPOSITED WITH THE U.S. POSTAL SERVICE  
"EXPRESS MAIL POST OFFICE TO ADDRESSEE"  
SERVICE UNDER 37 CFR 1.10 ON THE DATE  
INDICATED BELOW AND IS ADDRESSED TO:  
BOX PATENT APPLICATIONS, ASSISTANT  
COMMISSIONER FOR PATENTS, WASHINGTON,  
D.C. 20231.

EXPRESS MAIL NO: EL747059229US

DATE OF DEPOSIT: July 10, 2001

NAME: Alex Greene

SIGNATURE: 

PRELIMINARY AMENDMENT

Director, U.S. Patent and Trademark Office  
Washington, D.C. 20231

Sir:

Prior to the calculation of fees and examination of  
the present application, please enter the amendments and  
remarks set out below.

In the Claims:

Please cancel Claims 1 to 15.

Please add new Claims 16 to 50.

16. A method for compressing a digital image  
comprising a matrix of elements, each element comprising a  
plurality of digital components of different types for  
representing a pixel, the method comprising:

splitting the digital image into a plurality of  
blocks, and calculating for each block a group of discrete  
cosine transform (DCT) coefficients for the digital components  
of different types;

quantizing the DCT coefficients for each block using

099449-07004

In re Patent Application of:  
**BRUNA ET AL.**  
Serial No. **Not Yet Assigned**  
Filed: **Herewith**

---

a corresponding quantization table scaled by a gain factor for determining a target compression factor;

determining at least one energy measure of the digital image; and

estimating the gain factor as a function of the at least one energy measure, the function being determined experimentally according to the target compression factor.

17. A method according to Claim 16, wherein each group of DCT coefficients comprises at least one direct current (DC) coefficient and a plurality of alternating current (AC) coefficients; and wherein estimating the gain factor comprises:

estimating a first number of bits required to encode the AC coefficients of all the blocks using the quantization tables scaled by a pre-set factor as a first function of the at least one energy measure, the first function being determined experimentally according to the target compression factor;

calculating a second number of bits required to encode the DC coefficients of all the blocks using the quantization tables scaled by the pre-set factor;

estimating a basic compression factor provided by the quantization tables scaled by the pre-set factor according to the first number of bits and the second number of bits; and

estimating the gain factor as a second function of the basic compression factor, the second function being determined experimentally according to the target compression factor.

18. A method according to Claim 17, wherein the

In re Patent Application of:  
**BRUNA ET AL.**  
Serial No. **Not Yet Assigned**  
Filed: **Herewith**

---

first function is a linear function and the second function is a quadratic function.

19. A method according to Claim 17, wherein estimating the basic compression factor comprises:

estimating a third number of bits required to encode control values according to a number of elements of the digital image; and

dividing a sum of the first, second and third number of bits by the number of elements of the digital image.

20. A method according to Claim 17, further comprising:

storing a plurality of sets of parameters representing the second function, each set of parameters being associated with a corresponding value of the target compression factor;

selecting an image quality and determining a current value of the target compression factor as a function of the selected image quality; and

reading the parameters associated with the current value of the target compression factor for estimating the gain factor.

21. A method according to Claim 17, wherein the pre-set factor is determined experimentally according to the target compression factor.

22. A method according to Claim 16, wherein each element of the digital image comprises a luminance component, a first chrominance component, and a second chrominance

In re Patent Application of:  
**BRUNA ET AL.**  
Serial No. **Not Yet Assigned**  
Filed: **Herewith**

---

component.

23. A method according to Claim 22, wherein the at least one energy measure comprises a total energy measure equal to a sum of an energy measure of the luminance components, an energy measure of the first chrominance components and an energy measure of the second chrominance components.

24. A method according to Claim 23, wherein determining the at least one energy measure for each type of component comprises:

calculating a horizontal Sobel image and a vertical Sobel image by a convolution of the elements of the digital image comprising a type of component with a horizontal mask and a vertical mask, respectively;

calculating a total Sobel image by summing the horizontal Sobel image and the vertical Sobel image; and

summing an absolute value of each element of the total Sobel image.

25. A method according to Claim 24, wherein at least one quantization table is asymmetric along a horizontal direction and a vertical direction, the method further comprising multiplying the Sobel image associated with the at least one quantization table by a correction factor for compensating the asymmetry of the corresponding quantization table.

26. A method according to Claim 16, further comprising:



In re Patent Application of:  
**BRUNA ET AL.**  
Serial No. **Not Yet Assigned**  
Filed: **Herewith**

---

of alternating current (AC) coefficients;

quantizing the DCT coefficients for each block using a corresponding quantization table scaled by a gain factor for determining a target compression factor;

determining at least one energy measure of the digital image; and

estimating the gain factor as a function of the at least one energy measure by

estimating a first number of bits required to encode the AC coefficients of all the blocks using the quantization tables scaled by a pre-set factor as a first function of the at least one energy measure,

calculating a second number of bits required to encode the DC coefficients of all the blocks using the quantization tables scaled by the pre-set factor,

estimating a basic compression factor provided by the quantization tables scaled by the pre-set factor according to the first number of bits and the second number of bits, and

estimating the gain factor as a second function of the basic compression factor.

29. A method according to Claim 28, wherein the first and second functions are determined experimentally according to the target compression factor.

30. A method according to Claim 28, wherein the first function is a linear function and the second function is a quadratic function.

In re Patent Application of:  
**BRUNA ET AL.**  
Serial No. **Not Yet Assigned**  
Filed: **Herewith**

---

31. A method according to Claim 28, wherein estimating the basic compression factor comprises:

estimating a third number of bits required to encode control values according to a number of elements of the digital image; and

dividing a sum of the first, second and third number of bits by the number of elements of the digital image.

32. A method according to Claim 28, wherein each element of the digital image comprises a luminance component, a first chrominance component, and a second chrominance component.

33. A method according to Claim 32, wherein the at least one energy measure comprises a total energy measure equal to a sum of an energy measure of the luminance components, an energy measure of the first chrominance components and an energy measure of the second chrominance components.

34. A method according to Claim 33, wherein determining the at least one energy measure for each type of component comprises:

calculating a horizontal Sobel image and a vertical Sobel image by a convolution of the elements of the digital image comprising a type of component with a horizontal mask and a vertical mask, respectively;

calculating a total Sobel image by summing the horizontal Sobel image and the vertical Sobel image; and

summing an absolute value of each element of the total Sobel image.

In re Patent Application of:  
**BRUNA ET AL.**  
Serial No. **Not Yet Assigned**  
Filed: **Herewith**

---

35. A device for compressing a digital image comprising a matrix of elements, each element comprising a plurality of digital components of different types for representing a pixel, the device comprising:

discrete cosine transform (DCT) means for splitting the digital image into a plurality of blocks, and calculating for each block a group of coefficients for the digital components of different types;

quantization means connected to said DCT means for quantizing the DCT coefficients for each block using a corresponding quantization table scaled by a gain factor for achieving a target compression factor;

energy means for determining at least one energy measure of the digital image; and

estimation means for estimating the gain factor as a function of the at least one energy measure, the function being determined experimentally according to the target compression factor.

36. A device according to Claim 35, wherein said DCT means and said quantization means define a compression unit; wherein said estimation means comprises a processor for controlling compression of the digital image; the device further comprising:

a memory for storing the quantization tables; and

communication means for connecting said compression unit, said memory, said energy means and said processor together, said processor estimating the gain factor based upon a program stored in said memory.

37. A device according to Claim 35, wherein each



In re Patent Application of:  
**BRUNA ET AL.**  
Serial No. **Not Yet Assigned**  
Filed: **Herewith**

---

group of DCT coefficients comprises at least one direct current (DC) coefficient and a plurality of alternating current (AC) coefficients; and wherein said estimation means is for:

estimating a first number of bits required to encode the AC coefficients of all the blocks using the quantization tables scaled by a pre-set factor as a first function of the at least one energy measure, the first function being determined experimentally according to the target compression factor;

calculating a second number of bits required to encode the DC coefficients of all the blocks using the quantization tables scaled by the pre-set factor;

estimating a basic compression factor provided by the quantization tables scaled by the pre-set factor according to the first number of bits and the second number of bits; and

estimating the gain factor as a second function of the basic compression factor, the second function being determined experimentally according to the target compression factor.

38. A device according to Claim 37, wherein the first function is a linear function and the second function is a quadratic function.

39. A device according to Claim 37, wherein said estimation means for estimating the basic compression factor is further for:

estimating a third number of bits required to encode control values according to a number of elements of the digital image; and

In re Patent Application of:  
**BRUNA ET AL.**  
Serial No. **Not Yet Assigned**  
Filed: **Herewith**

---

dividing a sum of the first, second and third number of bits by the number of elements of the digital image.

40. A device according to Claim 35, wherein each element of the digital image comprises a luminance component, a first chrominance component, and a second chrominance component.

41. A device according to Claim 40, wherein the at least one energy measure comprises a total energy measure equal to a sum of an energy measure of the luminance components, an energy measure of the first chrominance components and an energy measure of the second chrominance components.

42. A device according to Claim 41, wherein said energy means is for:

calculating a horizontal Sobel image and a vertical Sobel image by a convolution of the elements of the digital image comprising a type of component with a horizontal mask and a vertical mask, respectively;

calculating a total Sobel image by summing the horizontal Sobel image and the vertical Sobel image; and

summing an absolute value of each element of the total Sobel image.

43. A digital still camera comprising:

an image acquisition unit for transmitting light corresponding to an image of scene;

a sensor unit connected to said image acquisition unit for providing a digital image of scene, the digital image

In re Patent Application of:  
**BRUNA ET AL.**  
Serial No. **Not Yet Assigned**  
Filed: **Herewith**

---

comprising a matrix of elements, each element comprising a plurality of digital components of different types for representing a pixel; and

a control device for compressing the digital image and comprising

a discrete cosine transform (DCT) circuit for splitting the digital image into a plurality of blocks, and calculating for each block a group of discrete cosine transform (DCT) coefficients for the digital components of different types,

a quantization circuit connected to said DCT circuit for quantizing the DCT coefficients for each block using a corresponding quantization table scaled by a gain factor for achieving a target compression factor,

an energy circuit for determining at least one energy measure of the digital image, and

a processor for estimating the gain factor as a function of the at least one energy measure, the function being determined experimentally according to the target compression factor.

44. A digital still camera according to Claim 43, wherein said DCT circuit and said quantization circuit define a compression unit; the device further comprising:

a memory for storing the quantization tables; and

a communication bus for connecting said compression unit, said memory, said energy circuit and said processor together, said processor estimating the gain factor based upon a program stored in said memory.

In re Patent Application of:  
**BRUNA ET AL.**  
Serial No. **Not Yet Assigned**  
Filed: **Herewith**

---

45. A digital still camera according to Claim 43, wherein each group of DCT coefficients comprises at least one DC coefficient and a plurality of AC coefficients; and wherein said estimation circuit is for:

estimating a first number of bits required to encode the AC coefficients of all the blocks using the quantization tables scaled by a pre-set factor as a first function of the at least one energy measure, the first function being determined experimentally according to the target compression factor;

calculating a second number of bits required to encode the DC coefficients of all the blocks using the quantization tables scaled by the pre-set factor;

estimating a basic compression factor provided by the quantization tables scaled by the pre-set factor according to the first number of bits and the second number of bits; and

estimating the gain factor as a second function of the basic compression factor, the second function being determined experimentally according to the target compression factor.

46. A digital still camera according to Claim 45, wherein the first function is a linear function and the second function is a quadratic function.

47. A digital still camera according to Claim 45, wherein said estimation circuit for estimating the basic compression factor is further for:

estimating a third number of bits required to encode control values according to a number of elements of the digital image; and

In re Patent Application of:  
**BRUNA ET AL.**  
Serial No. **Not Yet Assigned**  
Filed: **Herewith**

---

dividing a sum of the first, second and third number of bits by the number of elements of the digital image.

48. A digital still camera according to Claim 43, wherein each element of the digital image comprises a luminance component, a first chrominance component, and a second chrominance component.

49. A digital still camera according to Claim 48, wherein the at least one energy measure comprises a total energy measure equal to a sum of an energy measure of the luminance components, an energy measure of the first chrominance components and an energy measure of the second chrominance components.

50. A digital still camera according to Claim 49, wherein said energy circuit is for:

calculating a horizontal Sobel image and a vertical Sobel image by a convolution of the elements of the digital image comprising a type of component with a horizontal mask and a vertical mask, respectively;

calculating a total Sobel image by summing the horizontal Sobel image and the vertical Sobel image; and

summing an absolute value of each element of the total Sobel image.

#### REMARKS

It is believed that all of the claims are patentable over the prior art. For better readability and the Examiner's convenience, the newly submitted claims differ from the translated counterpart claims which are being canceled. The

In re Patent Application of:  
**BRUNA ET AL.**  
Serial No. **Not Yet Assigned**  
Filed: **Herewith**

---

newly submitted claims do not represent changes or amendments that narrow the claim scope for any reason related to the statutory requirements for patentability. Accordingly, after the Examiner completes a thorough examination and finds the claims patentable, a Notice of Allowance is respectfully requested in due course. Should the Examiner determine any minor informalities that need to be addressed, he is encouraged to contact the undersigned attorney at the telephone number below.

Respectfully submitted,



MICHAEL W. TAYLOR  
Reg. No. 43,182  
Allen, Dyer, Doppelt, Milbrath  
& Gilchrist, P.A.  
255 S. Orange Avenue, Suite 1401  
Post Office Box 3791  
Orlando, Florida 32802  
407-841-2330  
407-841-2343 fax  
Attorneys for Applicants